



ELECTRIC EXIT DEVICE KIT INSTALLATION INSTRUCTIONS AUTHORIZED EGRESS

K-126 AND K-226 THASE ENTERPRISE 8000 SERIES HAGER 4500 AND 4600 SERIES PDQ 6200 SERIES STANLEY QED100 AND QED200 SERIES

MONITORS THE USE OF THE PUSH BAR

Electrical Specifications:

SPDT Monitor Switch
Contacts Rated: 3A @ 125VAC
2A @ 30VDC

Wire Color Codes:

YELLOW - Common
RED - Normally Open
GRAY - Normally Closed

SWITCH 1

BLACK - Common
ORANGE - Normally Open
VIOLET - Normally Closed

SWITCH 2

Installation:

1. Separate the mechanism case from the baseplate assembly.
2. Attach the K-126 or K-226 Kit to the baseplate assembly through the existing holes using the supplied screws and lockwashers. Verify the switch arm is pre-actuated by the center link.
3. Route the lead wires along the outside edge of the baseplate assembly.
4. Attach the mechanism case to the baseplate assembly.
5. Secure the lead wires to the inside of the mechanism case using the supplied ty-wrap mount and ty-wrap.

